12MR2000X-NDY

Professional Mid Range Driver



KEY FEATURES


- · 4" Voice coil
- · 2000 Watts continuous program power
- 100 dB Sensitivity
- · 100 5,200 Hz

Nominal Diameter	12" (305 mm)
Nominal impedance	8 Ohm
Nominal Power Handling	1000 Watts
Continuous Program Power (RMS)	2000 Watts
Max Peak Power	4000 Watts
Sensitivity 2.83V at 1m	100 dB
Recommended High Pass Crossover* *For Full Power Handling	160 Hz * *12db Per Octave Crossover
1 of 1 det 1 ower Handeling	12db i ei Octave Ci 0330vei
Frequency Response	100 - 5,200 Hz
Frequency Response	100 - 5,200 Hz
Frequency Response Voice Coil Diameter	100 - 5,200 Hz 4" (100 mm)
Frequency Response Voice Coil Diameter Voice Coil Wire	100 - 5,200 Hz 4" (100 mm) CCAW
Frequency Response Voice Coil Diameter Voice Coil Wire Voice Coil Winding Depth	100 - 5,200 Hz 4" (100 mm) CCAW 18.20 mm

Equivalent Volume	Vas	35.9 l
Excursion (mathematical)***	Xmax	6.10 mm
Free Air Resonance	Fs	67.2 Hz
Mechanical Factor	Qms	16.7
Electrical Factor	Qes	0.32
Total Factor	Qts	0.31
Cone Area	Sd	573 cm ²
Mechanical Mass	Mms	71.5 g
Bl Factor	Bl	22.7 Tm
Dc Resistance	Re	5.4 Ohm
Inductance	Le	0.40 mH at 1 kHz
Mechanical Mass Without Air	Mmd	63.7 g
Mechanical Compliance	Cms	0.078 mm/N


Overall Diameter	12.28" (312 mm)
Front Mount Baffle Cutout	11.14" (283 mm)
Mounting Depth	4.47" (113.7 mm)
Overall Depth	4.95" (125.7 mm)
Net Weight	13.45 Lbs (7.0 kg)
Shipping Weight	17.60 Lbs (8.0 kg)
Carton Dimensions W x L x H	16.14" x 16.02" x 8.46" (410 x 407 x 215 mm)


Impedance Curve - Free Air




^{**}Xmax=(Voice coil winding depth-Magnetic Gap depth)/2+ Magnetic Gap Depth/4









PRV AUDIO USA (USA and Export)
POMPANO BEACH, FL
support@prvaudio.com
www.prvaudio.com