## D3220Ph

### Professional Compression Driver

# FRAZIL


#### **KEY FEATURES**


- · 3" Voice coil and 2" exit
- · 300 Watts continuous program power
- 108 dB Sensitivity
- · Phenolic diaphragm

Exit Throat Diameter	2" (50 mm)
Nominal Impedance	8 Ohm
Nominal Power Handling	150 Watts
Continuous Program Power (RMS)	300 Watts
Peak Power	600 Watts
Sensitivity 2.83V at 1m*	108 dB
Recommended High Pass Crossover**  **for Full Power Handling	800 Hz***  ***12 db/oct Crossover
Tor Face Ower Flandania	,
Frequency Response at -10dB	650 - 7,500Hz
<u> </u>	
Frequency Response at -10dB	650 - 7,500Hz
Frequency Response at -10dB  Voice Coil Diameter	<b>650 - 7,500Hz</b> 3" (76 mm)
Frequency Response at -10dB  Voice Coil Diameter  Voice Coil Wire	<b>650 - 7,500Hz</b> 3" (76 mm) CCAW
Frequency Response at -10dB  Voice Coil Diameter  Voice Coil Wire  Voice Coil Former Material	650 - 7,500Hz 3" (76 mm) CCAW Kapton <sup>®</sup>


Overall Diameter	5.71" (145 mm)
Overall Depth	3.0" (76 mm)
Mounting Bolt Circle	M6 x 4" (102 mm)
Net Weight	8.9 lbs (4.0 kg)
Shipping Weight	9.35 lbs (4.25 kg)
Carton Dimensions W x L x H	6.89" x 6.3" x 4.0" (175 x 160 x 102 mm)








#### Impedance Curve - Free Air



\*Frequency Response and Impedance curve Measured on WG14-50CR

#### Frequency Response Measured at 2.83V/1m



PRV AUDIO USA (USA and Export) POMPANO BEACH, FL support@prvaudio.com www.prvaudio.com