# **D275Ph-S**

# Professional Compression Driver




## **KEY FEATURES**


- 1"Exit driver
- · 200 Watts continuous program power
- · 106 dB Sensitivity
- · Phenolic diaphragm
- 500 6,500 diaphragm

Exit Throat Diameter	1" (25.4 mm)
Nominal Impedance	8 Ohm
Nominal Power Handling	100 Watts
Continuous Program Power (RMS)	200 Watts
Peak Power	400 Watts
Sensitivity 2.83V at 1m*	106 dB
Recommended High Pass Crossover**  **for Full Power Handling	600 Hz***  ***12 db/oct Crossover
TOI FULL POWER HARIUUR	12 UD/OCT CI 0550VEI
Frequency Response at -10dB	500 - 6,500Hz
Frequency Response at -10dB	500 - 6,500Hz
Frequency Response at -10dB  Voice Coil Diameter	<b>500 - 6,500Hz</b> 2" (51 mm)
Frequency Response at -10dB  Voice Coil Diameter  Voice Coil Wire	<b>500 - 6,500Hz</b> 2" (51 mm) Copper
Frequency Response at -10dB  Voice Coil Diameter  Voice Coil Wire  Voice Coil Former Material	500 - 6,500Hz 2" (51 mm) Copper Kapton <sup>®</sup>


Overall Diameter	4.61" (117 mm)
Overall Depth	2.67" (68 mm)
Mounting Thread	13/8" 18 TPI
Net Weight	1.91 lbs (0.87 kg)
Shipping Weight	2.03 lbs (0.92 kg)
Carton Dimensions W x L x H	5.0" x 5.0" x 3.0" (127 x 127 x 75 mm)








### Impedance Curve - Free Air



\*Frequency Response and Impedance curve Measured on WG14-25 S

#### Frequency Response Measured at 2.83V/1m



PRV AUDIO USA (USA and Export) POMPANO BEACH, FL support@prvaudio.com

www.prvaudio.com