# **D3220Ph-Nd**

## Professional Compression Driver




### **KEY FEATURES**


- · 3" Voice coil and 2" exit
- · 300 Watts continuous program power
- · 109 dB Sensitivity
- · Phenolic diaphragm
- · Light Weight Neodymium Magnet

Exit Throat Diameter	2" (50 mm)
Nominal Impedance	8 Ohm
Nominal Power Handling	150 Watts
Continuous Program Power (RMS)	300 Watts
Peak Power	600 Watts
Sensitivity 2.83V at 1m*	109 dB
Recommended High Pass Crossover**  **for Full Power Handling	800 Hz*** ***12 db/oct Crossover
TOI FULL FOWER HARIULING	12 UD/OCT CT 0550VET
Frequency Response at -10dB	600-7,500Hz
ū	
Frequency Response at -10dB	600-7,500Hz
Frequency Response at -10dB  Voice Coil Diameter	<b>600-7,500Hz</b> 3" (76 mm)
Frequency Response at -10dB  Voice Coil Diameter  Voice Coil Wire	600-7,500Hz 3" (76 mm) Cooper
Frequency Response at -10dB  Voice Coil Diameter  Voice Coil Wire  Voice Coil Former Material	600-7,500Hz 3" (76 mm) Cooper Kapton <sup>®</sup>


Overall Diameter	4.88"" (124 mm)
Overall Depth	2.21" (56 mm)
Mounting Bolt Circle	M6 x 4" (102 mm)
Net Weight	5.00 lbs (2.27 kg)
Shipping Weight	5.27 lbs (2.39 kg)
Carton Dimensions W x L x H	5.90" x 5.31" x 3.15" (150 x 135 x 80 mm)








#### Impedance Curve - Free Air



#### \*Frequency Response Measured on WG14-50CR

#### Frequency Response Measured at 2.83V/1m



PRV AUDIO USA (USA and Export)
POMPANO BEACH, FL
support@prvaudio.com
www.prvaudio.com